



Rear camera interface Ford MFD low 4" color screen 2012-2016

Art. Nr: RC-FOR-MFD

General

The Ford RC-FOR-MFD kit is a plug & play solution for adding an aftermarket rear camera or front camera into Ford vehicles equipped with the OEM 4" media screen.

No dealership programming is required and all connections are made behind the factory screen.



Additionally, both rear cameras can be forced to display on screen at any time, in any gear.

If you want to install aftermarket Rear & Front camera option you need an extra switch: RC-UNI-V

Features

- # Easy Plug n' Play install
- # Rear camera input
- # NTSC support
- # Trigger wire to force rear camera
- # Front camera input (optional)

Note

- Verify OEM 4" screen compatibility via model number AND termination resistance before ordering! (see image 2)
- See TAB compatibility for more information

Compatibility

Interface is compatible with the following models:

Ford:

C-max	2013-2014	Ford SYNC 1 (4")
Edge	2011-2017	Ford SYNC 1 (4")
Escape	2013-2015	Ford SYNC 1 (4")
Explorer	2011-2016	Ford SYNC 1 (4")
F-150	2013-2017	Ford SYNC 1 (4")
F-serie SuperDuty	2013-2016	Ford SYNC 1 (4")
Fiesta	2013-2015	Ford SYNC 1 (4")
Flex	2013-2016	Ford SYNC 1 (4")
Focus	2012-2016	Ford SYNC 1 (4")
Fusion	2013-2016	Ford SYNC 1 (4")
Taurus	2013-2016	Ford SYNC 1 (4")
Transit Connect	2015-2015	Ford SYNC 1 (4")
Transit	2014-2015	Ford SYNC 1 (4")

**Check your 4" MyFord system screen part number on the compatible list at our website*

**If your part number is not listed, camera compatibility can be verified by testing resistance*

Note

-2011-Current Ford & Lincoln vehicles w/ the 4" MyFord system and screen part

number on the compatible list below. This REQUIRES you to remove your existing screen to see the part number on the back BEFORE you purchase.
 -If your part number is not listed below, camera compatibility can be verified by testing resistance between pins 6 and 12 on the back of the display. If resistance reads ~75 Ω , display is camera compatible.

Screen part number which is working

BB5T-19C116-CJ	CK4T-18B955-CF	DA6T-18B955-BB	DS7T-18B955-CE
BB5T-19C116-CK	CM5T-18B955-AB	DA8T-18B955-CD	DS7T-18B955-CF
BT4T-19C116-CN	CM5T-18B955-AD	DA8T-18B955-CF	DT4T-19C116-CA
BT4T-19C116-CP	CM5T-18B955-CE	DB5T-19C116-CA	DT4T-19C116-CB
CB5T-19C116-CC	CM5T-18B955-CF	DB5T-19C116-CBT	DT4T-19C116-CC
CB5T-19C116-CD	CM5T-18B955-GB	DB5T-19C116-GA	DT4T-19C116-CD
CB5T-19C116-GC	CM5T-18B955-GD	DB5T-19C116-GB	DT4T-19C116-GB
CB5T-19C116-GD	CM5T-18B955-GE	DG1T-18B955-CD	DT4T-19C116-GD
CE8T-18B955-AA	CM5T-18B955-GF	DL3T-18B955-CC	EA8T-18B955-CB
CE8T-18B955-AD	CM5T-18B99-AD	DL3T-18B955-CD	EB5T-18B955-GA
CJ5T-18B955-GC	CM5T-18B99-GG	DL3T-18B955-CF	EB5T-18B955-GC
CJ5T-18B955-GE	D2BT-18B955-BE	DL3T-18B955-CG	EB5T-19C116-CA
CJ5T-18B955-GF	D2BT-18B955-BG	DM5T-18B955-CD	EB5T-19C116-CD
EG1T-18B955-CA	EJ5T-18B955-GB	EM5T-18B955-CB	EM5T-18B955-JB
EG1T-18B955-CD	EL3T-18B955-CE	EM5T-18B955-CC	ES7T-18B955-CA
EJ5T-18B955-CC	EM5T-18B955-CA	EM5T-18B955-CF	ES7T-18B955-CB
EJ5T-18B955-GA			
ET4T-18B955-CC	FB5T-19C116-CA	FR3T-18B955-CG	GL3T-18B955-CD
ET4T-19C116-CD	FB5T-19C116-GA	GK4T-18B955-CA	
ET4T-19C116-GG	FG1T-18B955-CA	GK4T-18B955-CB	